

SATCOM 342-01

BSC Filters Limited
10-11 Stirling Park, Bleriot Way
Clifton Moor, York, YO30 4WU. UK
Telephone: +44 (0) 1904 694250
E-mail: sales@bscfilters.com
Web-site: www.bscfilters.com

X BAND RECEIVE FILTER

BSC offer this X Band receive filter, designed to protect sensitive receivers from over 500 W transmit power whilst at the same time offering low insertion loss and incredible transmit rejection levels.

Passband:	7.25 to 7.75 GHz
Insertion Loss:	0.4 dB max
Return Loss:	19 dB min
Rejection from 7.9 to 8.4 GHz:	95 dB min
Power Handling:	500 W max
Operating temperature:	-40 to 85°C
Connectors:	UBR84 Flange
External Finish:	Gloss Black Gloss White – P1



Outline:

